

ALC650 application circuit Version 11

(To keep away from confusing chip version and circuit version, circuit version is named by number.)

Comparison between ALC650/ ALC202/ALC201/ ALC101

Comparison between ALC650/ ALC202/ALC201/ ALC101			ALC650	ALC202	ALC202A	ALC201	ALC201A	ALC101
	Built-In Amplifier	Pin-35/36	Front-Out	Line-Out	AMP-Out	Line-Out	AMP-Out	AMP
ALC650	Pin-35/36	Pin-39/41	Surr.-Out	AMP-Out	Line-Out	AMP-Out	Line-Out	None
ALC202A	Pin-35/36	Pin-43	Center-Out	GPIO0	GPIO0	Jack-Detect	Jack-Detect	X
ALC202	Pin-39/41	Pin-44	LFE-Out	GPIO1	GPIO1	X	X	X
ALC201A	Pin-35/36	Pin-31 (C27)	1uf	1uf	1uf	1uf	1uf	X
ALC201	Pin-39/41	Pin-32 (C29)	1uf	1uf	1uf	1uf	1uf	X
ALC101	Pin-35/36	Pin-34	Front-MIC	X	X	X	X	X
		Pin-39 (C44)	1uf	+100uf	1uf	+100uf	1uf	X
		Pin-41 (C45)	1uf	+100uf	1uf	+100uf	1uf	X
		Pin-45	GPIO0	ID0	X	ID0	ID0	X
		Pin-46	XTLSEL	ID1,XTLSEL	XTLSEL	ID1	ID1	XTLSEL
		Pin-47	SPDIFI (E version)	EAPD,JD	EAPD	EAPD	EAPD	EAPD
		Pin-48	SPDIFO	SPDIFO	SPDIFO	SPDIFO	SPDIFO	X


Revision History


- version G (1) Modify MIC bias circuits in "Analog_IO1.sch" to improve MIC performance
- version 07 (1) For ALC650 E version, Vrefout can be disabled in jack share mode, use Vrefout to bias microphone input. ("Analog_IO1.sch")
(2) Modify S/PDIF-In circuits to accommodate optical receiver and RCA input. (ALC650 E version)
- version 08 (1) Improve GPIO control circuit for MIC bias voltage
(2) Suggest low cost S/PDIF optical fiber component
- version 09 (1) Delete demo circuit of TDA1308.
(2) Suggest a low cost external S/PDIF cable module in page 5
(3) Add a series resistor R52=22 ohm at SDIN in page 1
- version 10 (1) In '5_SPDIF_Cable.SCH', receiver TORX176/173 is instead of TORX178/179.
- version 11 (1) XTLSEL (pin-46) should be pulled low to digital GND if 14.318MHz external clock is the clock source .
(2) S/PDIF-IN bias resistor R7 is 100K for E version, 75K for F version (4_SPDIF_IO.SCH, 5_SPDIF_Cable.SCH)

Title		ALC650	
Size	Document Number	Preface	
Custom			Rev 11
Date:	Friday, October 25, 2002	Sheet	0 of 5

R47, R49 and C14 can bias external clock to acceptable level once the driving strength of external clock is weak.




The recommended regulator must supply at least 200mA output current to prevent from overheating.






****Those resistors in Block-A are used to fine-tune performance, system designer had better keep those resistors.**


If LINE-IN is designed to be shared with Surround-Out, keep 2/3 are floated




option 1: For ALC650 rev.D, select this bias circuit to share MIC-In and CEN/LFE-Out



If MIC-IN is designed to be shared with CEN/LFE-Out, keep 2/3 are floated





(R16, R17 not mounted if front panel header mounted)




If AVDD is supplied by 78L05 has only 100mA current, change R16 and R17 to 20ohm to limit current consumption.


Block-A: to fine tune performance, system designer had better keep those resisters.



Block-B (Front panel header)




Block-C (6 channel analog output in Mini Din connector)




Block-D (Option: for different definition about LFE and Center)

(ALC650 rev.E can switch LFE and Center output, this block can be eliminated.)



MDIN9




Realtek Semiconductor, Corp.

Title		ALC650	
Size B	Document Number	Rev 4/1	
Date: Friday, October 25, 2002		Sheet 3	of 5

Option (I): S/PDIF signal use RCA connector

+ Line Driver/ Receiver (is suitable for long transmission line)

The T1 transformer should be capable of operating from 1.5M to 7MHz
(with lower shunt capacitor is preferred)




Note:

Option(I) /(II) /(III) are optional


Option (III): Without Line Driver/ Receiver

Use R3 and R8: Guaranteed transmission distance <= 7 feet

Use T1,R5,R6: At least 10 feet of transmission distance



Option (II): S/PDIF signal use fiber optic transmitter and receiver module



S/PDIF Output: ALC650, ALC202, ALC201

S/PDIF Input: ALC650 rev.E or later only

Output level VLevel=+3.3V, R9=0 ohm, R11=removed


Output level VLevel=+5.0V, R9=1k ohm, and R11=2k ohm should be mounted

Realtek Semiconductor, Corp.

Title			ALC650
Size	Custom	Document Number	S/PDIF Input/Output
Date:	Friday, October 25, 2002	Sheet	4 of 5



Rev 11

*The S/PDIF cable module should be confirmed by Realtek.




28AWG copper line
Recommended maximum length is less than 6 inches

74HC04 is used to improve sensitivity for S/PDIF-In signal, it can be removed and R10=0 if only optical receiver is used.



No Automatic Threshold Control to stabilize output, it is not suitable for connecting to RCA signal



Be aware of that ALC650 E and later version only support one pin of S/PDIF-In input, so the operation between optical receiver and RCA connector is exclusive.

It means that optical receiver and RCA connector can not input signal at the same time.

Realtek Semiconductor, Corp.			
Title			
ALC650			
Size	Document Number	Rev	
Custom	S/PDIF Cable Module	11	
Date:	Friday, October 25, 2002	Sheet	5 of 5